

## 捣固锤 (不适用于CE和ANSI/NA市场)

FUJI捣固锤重量轻, 功率大, 冲程范围从50mm到127mm。FUJI捣固锤对于任何黑色及有色金属铸造的捣固工作均非常卓越, 非旋转型捣固锤对不规则形状的端部也很有效。



FR-18B~25B



FR-18L~32



型号	频率	活塞直径		冲程		头部直径		总长度		重量		耗气量 (负载)		空气软管尺寸	
		mm	in	mm	in	mm	in	mm	in	kg	lb	m <sup>3</sup> /min	ft <sup>3</sup> /min	mm	in
FR-18B	30	18.0	45/64	50	1 31/32	41	1 5/8	280 (383)	11 1/32 (15 5/64)	1.5	3.3	0.40	14.1	9.5	3/8
FR-22B	17	22.0	55/64	64	2 33/64	51	2 1/32	350 (451)	13 25/32 (17 3/4)	3.0	6.6	0.50	17.7	9.5	3/8
FR-25B	13	25.4	1	83	3 17/64	67	2 41/64	506 (597)	19 59/64 (23 1/2)	5.5	12.1	0.70	24.7	12.7	1/2
FR-18L	30	18.0	45/64	50	1 31/32	41	1 5/8	558 (523)	21 31/32 (20 19/32)	2.0	4.4	0.40	14.1	9.5	3/8
FR-22L	17	22.0	55/64	64	2 33/64	51	2 1/32	633 (600)	24 59/64 (23 5/8)	3.3	7.2	0.50	17.7	9.5	3/8
FR-25L	13	25.4	1	83	3 17/64	67	2 41/64	1,043 (1,005)	41 1/16 (39 9/16)	6.0	13.2	0.70	24.7	12.7	1/2
FR-32	12	32.0	1 17/64	127	5	75	2 61/64	1,086 (1,090)	42 3/4 (42 29/32)	10.0	22.0	0.80	28.2	12.7	1/2

进气螺纹PT 1/4" (除FR-25B, FR-25L, FR-32: 3/8")